

SD-10G AERO

Procedure to obtain 2-Position operated Flaperons (Ailerons) controlled by a 3-position switch using the SD-10G transmitter.

Select **SYSTEM** using the Navigation Pad and Yes/+ key. Press **ENTER**.

Scroll down to **TYPE**. Set it to read: **AERO**; **WING** >NORMAL; **AILERON** >2; **FLAP** >1; **TAIL** >NORMAL; **THROTTLE** >1. Press **END**.

Scroll down to **CHANNEL ASSIGN**. Press **ENTER**. Make the following assignments:

F-MODE 1 >14; F-MODE 2 >13; FLAP 1 >14; FLAP 2 >13; C-MIX 1 >14 >OR >13;

C-MIX 2 >14 >OR >13. Press **END** key twice.

Select **SURFACE**. Press **ENTER**. Set Servo Reversing for correct Aileron, Elevator, etc., operation.

Turn **ON** switch #14. Set **FLAP EPA 1 50%**. Turn **ON** switch #13. Set **EPA 2 100%**. Press **END**.

Scroll Down to **F-MODE**. Press **ENTER**. Scroll down to **C-MIX (#18)** Press **ENTER**.

Turn ON Switch #14. Set C-MIX 1 as follows:

F-MODE(1)

C-MIX >1

COMMON >SEP

MASTER >FL

SLAVE >LA

POINT >9

RATE >50%

Turn ON Switch #13. Set C-Mix 1 the same as above.

Select **C-MIX 2**. **Turn ON Switch #13**. Set C-MIX 2 as follows:

F-MODE(2)

C-MIX >2

COMMON >SEP

MASTER >FL

SLAVE >RA

POINT >9

RATE >-50% Press **END** key.

NOTE: Polarity determines the direction of servo throw. These are all trail values. Fine tune setup as needed after completion of setup. Flaperons (Ailerons) operate with half value with Switch #14 ON, and at full value with Switch #13 ON.

Scroll down to **VR ASSIGN (#19)**. Press **ENTER**. **Make All items read: > - - -** Press **END**.

Channel outputs are: 01 >EL; 02 >LA; 03 >TH; 04 >RU; 05 >GE; 06 >RA; 07 >FL (if used); 08 >A3; 09 >A2; 10 >A1.

Jack R. Albrecht
Airtronics Technical Support
15 July 2009